

Haiwell PLC User Manual A Series Card-type PLC

Communication Module User Manual & Application Case



Contents

Communication Expansion Module A01RS User Manual

1. Product model list and dimension	
2. Indicator description	3
3. Environmental specification for product	
4. Module terminal wiring diagram	
5. A01RS wiring diagram (RS485&RS232)	4
6. Module connection method	4

Communication Expansion Module A01RS Application Example

1. Module power supply	5
2. Applicable host PLC	5
3. Hardware configuration and communication port number	5
4. Communication protocol	5
5. Haiwellbus communication example description:	6
5.1 Communication between two Haiwell host PLCs	6
5.2 example of a disconnection alarm program for slave communication	8
6. Modbus communication example introduction:	8
6.1 Communicate with H08RC thermal resistance IO communication module	8
6.2 Read and Write the inverter frequency example	8
7. Typical free protocol applications:	9
7.1 Tn=0, Rn>0, only receive data	9
7.2 Tn $>$ 0, Rn=0, only send data	11
7.3 Tn $>$ 0, Rn $>$ 0, for example, communication with YUDIAN instruments by AIBUS	11
8. The system registers of communication timeout time, communication instruction execution interval, communication	ו port
character receiving timeout time and application introduction	13
9. When PLC is used as slave station, there is no need to to write any communication program, and supporting a varie	ety of
human-machine interfaces and configuration softwares	15
10. How to judge the communication failure and program analysis when PLC is used as slave	17
11. Check-code calculator usage introduction	17
12. The introduction of supportive baud rate, data format and communication instructions when PLC communication port is	used
as a master/slave station	18
12.1 PLC communication port used as a master station:	18
Supported by AC, AT, AH series host PLC communication port:	18
12.2 PLC communication port used as a slave station:	18
13. PLC communication common problems	19

Communication Expansion Module A01RS User Manual

1. Product model list and dimension

Models	Power Consumption(24VDC)	Dimension(W \times H \times D)
A01RS	DC24V~0.1A MAX	25×95×65 mm



1. COM channel indicator	6. Module connection buckle
2. PWR power indicator, LINK module communication indicator	7. Module positioning hole
3. Terminal definition	8. Module expansion port
4. Removable terminal	9. 35mm DIN guide rail
5. Track Buckle	

2. Indicator description

- PWR: power indicator. green, constant light Power normal; Not light Power abnormal.
- LINK: indicator constant lighting MPU has identified the module; indicator Green jitter Module is communicating with MPU. Red jitter quickly Firmware not completed.
- COM indicator digit 0: Indicates that communication port 0 is RS232 or RS485 communication mode, when it is used as a master, it sends command with flickering; when it is used as a slave, it replies data with flickering

3. Environmental specification for product

Items	Environment Specifications
Temperature/Humidity	Operating temperature:0~+55℃ Storage temperature:-25~+70℃ Humidity: 5~95%RH, No condensation
Vibration Resistance	10~57 HZ, amplitude=0.075mm, 57HZ~150HZ acceleration=1G, 10 times each for X-axis, Y-axis and Z-axis
Impact Resistance	15G, duration=11ms, 6 times each for X-axis, Y-axis and Z-axis
Interference Immunity	DC EFT: ±2500V
Landing	Third earthing (not common to high voltage systems)
Over Voltage Resistance	1500V AC/1min between AC terminal and PE terminal, 500VAC/1min between DC terminal and PE terminal
Insulation Impedance	Between AC terminal and PE terminal @500VDC,>=5MΩ ,all input/output points to PE terminal @500VDC
Operating environment	Avoid dust, moisture, corrosion, electric shock and external shocks
Isolation mode	No isolation between channels, use optoelectronic isolation for the communication interface and the internal power supply

4. Module terminal wiring diagram



GND

Shielding wire

Single-end grounding



6. Module connection method

Shielding wire

Single-end grounding

B-

The PLC should be secured to an enclosed cabinet while mounting. For heat dissipation, make sure to provide a minimum clearance of 50mm between the unit and all sides of the cabinet. (See the figure.)

GND

Rail Mounting: Use standard 35 mm rail.

Connecting Extended Module

Join lower right parallel interface of Last module (Host or Extension Module) to the lower right of the parallel interface of next module, then tight with two buckles on top and bottom.

The interface of the right side module is left for extension interface for next extension module.



Communication Expansion Module A01RS Application Example

1. Module power supply

Module is directly hung behind the host PLC and powered by parallel port, no need to take external power supply.

2. Applicable host PLC

AT, AH series PLC can be expanded with communication modules, the maximum can be expanded with 3 A01RS modules.

3. Hardware configuration and communication port number

Host PLC is built-in 2 communication ports, respectively are ethernet port and COM2 for RS485 port; the A + B- terminal on terminal row. Communication expansion module A01RS not only can be used as 232, but also can be used as 485, no program definition required. It depends on the external wiring, A01RS can be used as 485 when connected to 485 port or it can be used as 232 when connected to 232 port, but it only can choose one or the other one.



When the communication module is expanded, the communication port closest to the host PLC is COM3, next is COM4 and last is COM5. The position of communication module can be random, and the communication port number can be viewed in the hardware configuration, as shown in the figure below:

Index	Module type	X Component	Y Component	Al Component	AQ Component	Other	Description
0	AT16S0R	X0 - X7	Y0 - Y7	3		COM1-2 HSC0-1	CPU module 8*DI 8*DO relay D
1	A01RS					Port3	1 serial port RS232/RS485 sup
2	A01RS					Port4	1 serial port RS232/RS485 sup
3	A01RS					Port5	1 serial port RS232/RS485 sup

4. Communication protocol

It is built-in Modbus RTU / ASCII protocol, freedom communication protocol and Haiwellbus high-speed communication protocol of Haiwell company(each port supports the above protocols). One communication port can take different baud rates, different data formats, different communication protocols at the same time, as you can see in the following network diagram, two 485 networks can be normal and efficient communication.



5. Haiwellbus communication example description:

5.1 Communication between two Haiwell host PLCs

This example shows the communication between two host PLCs. It is known that communication baud rate is 19200 between the master and slave PLC, data format is N 8 2 RTU, and slave station number is 2.

 Master reads 2 # slave data: for example, read X0 of slave into master M0; read X3 of slave into master M11, etc., as follows:

Index	Component read from slave	Component write to master
1	X0	M10
2	X3	M11
3	V11	V80
4	V12	V81
5	AIO	V20
6	Al1	V21

② Master writes 2 # slave data: for example, write V0 of master into slave V100; write V50 of master into slave V102, etc., as follows:

Index	Component read from master	Component write to slave	
1	X0	M100	
2	X1	M101	
3	V0	V100	
4	V50	V102	
5	Y4	MO	
6	Y5	YO	
7	V60	V200	
8	V61	V201	

Programming ideas:

In the Haiwell PLC programming software, set up Haiwellbus read communication table, special floating-point and 32-bit data occupy two consecutive addresses, if the master wants to write the floating-point or 32-bit data into the slave, it needs to fill two consecutive registers, such as write V11V12 into V80V81, as follows:

Haiwel	lbus read table				
int	Table name: Read 2# slave data				
Index	Component read from slave	Component write to master	Component comments		7
1	XO	M10			Append
2	X3	M11			
3	V11	V80			Insert
4	V12	V81			Dalata
5	AIO	V20			Delete
6	AI1	V21			Move up
					Move down
omme	ents			Password:]
He	lp.			ОК	Cancel

In the Haiwell PLC programming software, set up Haiwellbus write communication table, as follows:

st	1			
ndex	Component read from master	Component write to slave	Component comments	Annend
1	X0	M100		reports
2	X1	M101		Insert
3	V0	V100		
4	V50	V102		Delete
5	Y4	MO		
6	Y5	YO		Move up
1	V60	V200		
8	V61	V201		Move down
omme	ents		Password Confirm password	

After the table is established, use HWRD and HWWR instructions, and enter the slave address in the "Slave" terminal of the instructions. In this case, the slave PLC address is "2", directly input the table name in the "Table", or double-click the terminal to select the established table. "Port "is the communication port number, as described in the second point above, "2" indicates the master's COM2 for 485 communication port. In this way, the communication program which reads and writes from the slave is completed, as follows:

		En Out	_M5
	2_	Slave	Teau UK
	Read 2# slave data_	Table	
	2_	Port	
		En Out	_M6 write ok
	2_	Slave	12220003600
	write 2# slave date_	Table	
	2_	Port	
1			

5.2 example of a disconnection alarm program for slave communication

Judging the communication error code situation through the communication instruction "Out" terminal. "Out" terminal has power indicating that communication is very good without error; "Out" terminal has no power indicating that the communication does not succeed, in this way, just check the slave parameter settings and networking wiring; "Out" terminal flashes to indicate a communication error code, and occasional error code in communications does not matter, communication may be disturbed, therefore, it is possible to check whether the outside uses shielded twisted pair or not, also, multiple slaves need to be in the way of "hand in hand" or add communication solator S01GL from Haiwell company. The following is an example of a disconnection alarm program for slave communication:

M5 Fead ok	In TON.1s Ut T0 2# slave C 5_ Pt TV	Communication

Communication disconnection time can be set according to the actual, the above when M5 is more than 5 seconds in OFF state, T0 coil will indicates communication disconnection alarm.

6. Modbus communication example introduction:

In this example, the host PLC is expanded with a communication expansion module A01RS, communication port is 3, the communication port is connected to a Haiwell thermal resistance module H08RC and a inverter:

6.1 Communicate with H08RC thermal resistance IO communication module

H08RC module is built-in RS485 port which can be used for remote IO, supporting Modbus RTU / ASCII protocol, communication parameters is 19200 N 8 2 RTU, station number is 1 #, from the programming software online help - hardware manual - expansion module parameters, we can see the 8 temperature values are stored in Modbus start address 10 ~ 17H, which is decimal 16 ~ 23.

6.2 Read and Write the inverter frequency example

Inverter, 9600 E 7 1 ASCII, station No. 2 #. It is required to read and write the inverter frequency, from the inverter manual we can see that the parameter address of the setting frequency is 2001H, decimal 8193, and the parameter address of the operating frequency is 2103H, decimal 8451. In this way, write the program as follows:

//Network 3 Communication parameters 19200,N,8,2, Slave 1#, eigeht temperature modbus address are 10-17H. The decimal system are 16-23





//Network 4 inverter,9600 E 7 1 ASCII, Slave 2#.Setting frequency address is 2001H, The decimal system is 8193. Run frequency address is 2103H. The decimal system is 8451.

Port = 3, in this example, it indicates the communication port of S01RS. 8193 can be quickly entered, such as put the mouse on the "Write" terminal, then it can directly enter 0x2001.

7. Typical free protocol applications:

Serial communication COMM instruction is divided into high-low byte mode and low byte mode. Base on sending and receiving terms, it can seperate for 3 types: only sending, only receiving and waiting for data receiving after sending commands. For more detail of instructions introduction, you can refer to the software online help. As for free communication, the essence is to understand the communication protocol, the following we will introduce the typical application of COMM instruction.

7.1 Tn=0, Rn>0, only receive data

Only receive data, for example, PLC communicates with the weighing instrument, it is known that the weighing instrument has 485 port, the baud rate is 9600, data format is E 7 1 ASCII, the weighing instrument generally has two modes, query mode and continuous sending mode. Continuous sending mode, it indicates that the instrument intermittently send the current weight to the communication port, so as long as the PLC side is responsible for receiving data.

It is known that the weighing instrument sends 18 bytes of data to the communication port for each time, and the 18 bytes respectively represent the specific meanings as follows:

Byte order	ASCII symbol	Hexadecimal number	Meaning
	OL	4FH 4CH	Overrange
1~2	ST	53H 54H	Static load
	US	55H 53H	Dynamic load
3	,	2CH	Separator
A. F.	NT	4EH 54H	Net weight
4~0	GS	47H 53H	Gross weight
6	,	2CH	Separator
7	+	2BH	Positive sign
	-	2DH	Negative sign
	0~9	30H-39H	Data
8~14	""	20H	Space
		2EH	Decimal point

15~16	Kg	4BH 67H	Kilo
15~10	"Т"	54H 20H	Ton
17	CR	0DH	Enter
18	LF	0AH	Line feed

Assuming that the net weight of weighing instrument is 1.23Kg, then the weighing instrument will send 18 bytes of data to the PLC according to the above format, the data is in hexadecimal:

53 54 2C 4E 54 2C 2B 20 20 20 31 2E 32 33 4B 67 0D 0A

The above data indicating the weight is 2B 20 20 20 31 2E 32 33, it represents 1.23 Kg. 2B is the "+" sign, 20 is a space, 2E is the decimal point, $30 \sim 39H$ is the character $0 \sim 9$. So we just use the COMM instruction to receive the 18 bytes back, and parse out the weight we want. In this way, we write the COMM instruction below:



When PLC is running, and COMM instruction is scanned, since Tn = 0, there is no need to send command. Therefore, COMM instruction will be in receiving status according to baud rate and data format defined by protocol, at this moment, when the weighing instrument sends the data of 53 54 2C 4E 54 2C 2B 20 20 20 31 2E 32 33 4B 67 0D 0A, the COMM instruction will receive the data, and store it in the start register of V200, when the data is stored, first stored in the low byte of the register, then stored the high byte of the register, as follows:

 0A0D	674B	3332	2E31	2020	202B	2C54	4E2C	5453
 V208	V207	V206	V205	V204	V203	V202	V201	V200

From the above we can see that we want the data in V203 ~ 206, these four registers, a total of 8 bytes. The next is data analysis, Haiwell has a very convenient instruction of character to floating point, that is, CTOF. So we write the program as follows, and get the simulation results through communication simulator running:

🧷 Communicatio	on simulation - Com2 (1)				
Com2 (1)					
Help	PC Port: COM1 ~ Pause	Clear		Device manager Use real serial	port
Wait for respons	se (COMM V1200, 0, 18, 116, 2, M13, M14, V	/200)	Index	Communication instruction	Data format
Response 53 54	1 2C 4E 54 2C 2B 20 20 20 31 2E 32 33 4B	67 0D 0A		COMM V 1200, 0, 18, 116, 2, M13, M14, V200	9000,e,7,1
Wait for respons	e (COMM V1200, 0, 18, 116, 2, M13, M14, V	/200)			
		~			
Hex OASCII	CRC LRC BCC SUM Cr Lf	Response			
53 54 2C 4E 54 2	2C 2B 20 20 20 31 2E 32 33 4B 67 0D 0A	^			
		~	<		>

Click on the "simulation", open the communication simulation in the debug menu, fill in the data in the answering area, click on the "answer" to simulate the communication program, if the serial interface of computer is actually connected to instrumentation, you can check the "use the actual serial port" so that the software can co-simulation with the actual instrument, very convenient. The final simulation program is as follows:



7.2 Tn>0, Rn=0, only send data

For example, when the values of the register V300 in the PLC are respectively different values, then it sends different data contents to the serial port, for example:

V300 = 1, then send the 6 bytes data of V1000 ~ 1002 to the communication port;

V300 = 2, then send the 8 bytes data of V1010 ~ 1013 to the communication port;



7.3 Tn>0, Rn>0, for example, communication with YUDIAN instruments by AIBUS

Al instrument uses hexadecimal data format to represent a variety of instruction codes and data. Al instrument only has two standard communication instruction, one is read instruction, the other is write instruction. As follows:

Read: address code + 52H (82) + parameter code to read + 0 + 0 + check code

Write: address code + 43H (67) + the parameter code to be written + low byte of written data + high byte of written data + check code

Return data: The instrument returns the following 10 bytes of data no matter for writing or reading:

Measured value PV + setting value SV + output value MV and alarm status + parameter value to be read / written+ check code

In this case, the instrument address is 1, baud rate is 9600, data format is N 8 1. When reading the current temperature, assume

the current temperature is 254.1 °C (2541 = 0x9ED), then send and reply data as follows (why the following data is the content for sending and replying , please refer to the AI instrument manual agreement section):

Send:	81	81	52	00	00	00	53	00		
Reply:	ED	09	00	00	00	60	00	00	EE	69

In general, read commands are fixed. Haiwell provides a very convenient initialized data table: it is initial register value table, the commands which will be sent are filled in the initial register value table, in this case, the starting address is V1020, the length is 4, a total of 8 bytes, as follows:

 00 53	00 00	00 52	81 81
 V1023	V1022	V1021	V1020

The COMM instruction has two modes, one is high-low byte mode, first, sending the low-byte data of the start address, then, sending the high-byte, and so on. The other is the low-byte mode of COMM.LIB. You can double-click to set the COMM instruction, it only sends the low-byte data of the register. In this example of high-low byte mode, first, send the low-byte 81H of V1020, then send high-byte 81H, send the low-byte 52H of V1021, then send high-byte 00H of V1021 and so on.

The following is the initial register values table of "read AI instrument commands":

Initial r	egister table				
Power-	Table name: Rea	ad Al instrument	S	tart component 1020 O Decimal Hex O F Length: 4 (0 to 200) O Character	loat
Index	Component	16bits value	32bits value	Component comments	
1	V1020	0x8181	0x00528181		
2	V1021	0x0052	0x00000052		
3	V1022	0x0000	0x00530000		
4	V1023	0x0053	0x00000053		
Comme	ents				
				Passwor	d:
				Confirm non-swor	d
					u.
Un	In Ch	ock codo colculator			Canaal
He	ip Ci	eck code calculator			Cancer

Then according to the regulation of the instrument, we write the COMM instruction, and the simulation is carried out as follows:

Componer	nt state table - Sta	atus table1					
Status ta	ble1					CC	MM
Component	16bits value	32bits value		C	Component comm \land	En	Out read success
V50	2541	25 <mark>4</mark> 1			Measurement PV	V1020=-32383Txd	Err_M21
V51	0x0000	0x6000000				Sending data sta	read failed
V52	0x6000	0x00006000				°— Tn	Rxd Measurement
V53	0x0000	0x69EE0000				10Rn	in our official and the second s
V54	0x69EE	0x000069EE				100	
						120_ Proto	col
					. *	2 Port	
F					,	TOIL	
Communic	ation simulation -	Com2 (1)					
Com2 (1)	6						
Help	PC Port:	COM1 🗸 🗌 Pause	Clear		Device manager	Use real serial	port
	Second and the	1.00 000 10 000 00 00 00 00	~	Index	Communication in	struction	Data format
Send (COMN 81 81 52 00 0 Wait for resp	V1020, 8, 10, 120 00 00 53 00 0056), 2, M20, M21, V50)		I	COMM V1020, 8, 1	0, 120, 2, M20, M21, V50	9600,n,8,1
Response E	D 09 00 00 00 60 0	00 00 EE 69					
0	14000 0 40 400	0 1100 1104 1/501		-			
Send (COMM 81 81 52 00 1	1 V1020, 8, 10, 120 00 00 53 00), 2, M20, M21, V50)		_			
Wait for resp	onse			-			
			X	-			
●Hex ○A	SCII CRC LRC	BCC SUM Cr Lf	Response	_			
ED 09 00 00	00 60 00 00 EE 69	1	~				
				-			
			×.,	<			

When PLC is running, COMM instruction is scanned, because Tn=8> 0, COMM instruction will send command to communication port 2 according to the baud rate and data format defined by protocol: 81 81 52 00 00 00 53 00, after sending completed, judge Rn=10> 0, then it turns into the receiving state. After receiving the command, it will reply the data: ED 09 00 00 00 60 00 00 EE 69, the data received by the PLC will be placed in the starting register of V50, first it will be stored in the low byte of V50, and then it will be stored in the high byte of V50, low byte of V51, high byte of V51 and so on, when receiving data of Rn=10, OUT terminal is ON, marking the success of this communication

 69 EE	00 00	60 00	00 00	09 ED
 V54	V53	V52	V51	V50

Received data is arranged as shown above, hexadecimal 09ED is the decimal number 2541, a decimal precision, which is the actual 254.1 °C.

8. The system registers of communication timeout time, communication instruction execution interval, communication port character receiving timeout time and application introduction

Communication timeout time

The unit is ms, the default is 200, that means 200ms, indicating the time which is waiting for the response and replying data from the slave, after PLC sending commands to communication port. Communication timeout is used for PLC master station, there is no need to use this communication system register when PLC is used as a slave station.

System register	Note	Read/write	Power-off preserve	Default value
SV45	COM1 and Ethernet communication timeout time, unit: ms	R/W	Yes	200
SV47	COM2 communication timeout time, unit: ms	R/W	Yes	200

SV55	COM3 communication timeout time, unit: ms	R/W	Yes	200
SV57	COM4 communication timeout time, unit: ms	R/W	Yes	200
SV59	COM5 communication timeout time, unit: ms	R/W	Yes	200

In general, the value is default, it is generally used in the situation when some slave instruments response data slowly, for example, when slave instrument receives the commands from PLC, it will take 0.5 second to reply the data, at this time, you need to increase the communication timeout time. If you need to increase the communication timeout time, there are two ways for settings:

① In the PLC program, use MOV assignment instruction to assign values to system registers, such as COM2 communication timeout time setting.

	Er	MOV	8 <u>1999</u>
	500 In	Out	_SV47 COM2 communicate over

2 After PLC online, in the menu bar - PLC pull-down option - communication parameters settings-set the communication timeout time.

ut 200	
	COM1 Parametere: 10200 N 9 1 PTI
ut. 200	CONTEnanteleis. 19200,14,0,1 RTO
ut: 200	COM2 Parameters: 19200,N,8,2 RTU
ameter	
M1 ~	timeout: 200 🗸 r
M1 M2	
M3	
MA V	
	ut: 200 ort: Com1 matter M1 ~ M2 ~ M3 ~

③ Serial debugging tools can record the data's interval time from sending to replying. Therefore, it is recommended that before PLC and instruments communication, you can use the serial port debugging tools to communicate with instruments, so that we can confirm the instrument station number, baud rate, data format, and the Modbus addresses to be read and written, response time and so on. In this way, writing PLC communication instruction will be easier. For example, the following figure of 16ms:

🖀 Commix 1.4 —	□ ×
Port: COM1 - BaudRate: 19200 - Apply DTR RTS	Close Port
DataBits: 8 💌 Parity: None 💌 StopBits: 2 💌 🗂 No CF	RC Pause
Input HEX Show HEX Input ASC Show ASC 🔽 Ignore Space 🔽 New Line 🔽 Show Interval –	Clear
01 03 02 00 00 01	s) Send
	 Iv by Enter
01 03 02 00 00 01	^
(31 ms) 01 83 09 81 36	
	×

Communication instruction execution interval

The interval time defaults to 0, PLC will execute next one immediately after one communication instruction has been executed. If some devices are not allowed or can not receive such a fast communication frequency, it need to set communication interval through MOV instruction assignment.

System register	Note	Read/write	Power-off preserve	Default value
SV141	COM1 communication instruction execution interval, unit: ms	R/W	Yes	0
SV833	COM2 communication instruction execution interval, unit: ms	R/W	Yes	0
SV834	COM3 communication instruction execution interval, unit: ms	R/W	Yes	0
SV835	COM4 communication instruction execution interval, unit: ms	R/W	Yes	0
SV836	COM5 communication instruction execution interval, unit: ms	R/W	Yes	0

Note:

- Communication time of S series PLC's all communication ports is set by SV141, CTHN four series can be set separately.
- Communication instruction execution interval is used for PLC master station, there is no need to use this communication system register when PLC is used as a slave station.

Communication port character receiving timeout time

There will be a situation in the process of communication with instruments, that is, intervals between communication characters of some instruments are not standard, or a frame data is longer and divided into multiple returns, the intervals between character frames are larger, so that the PLC can not receive the complete data frames and the instruction will judge that the communication fails. To this situation, Haiwell conveniently provides a system register used to set the communication port character receiving timeout time. At this time, the character receiving timeout time can be set. Set the communication port character receiving timeout time through MOV instruction assignment.

System register	Note	Read/write	Power-off preserve	Default value
SV851	COM1 communication port character receiving timeout time, unit: ms	R/W	Yes	0
SV852	COM2 communication port character receiving timeout time, unit: ms	R/W	Yes	0
SV853	COM3 communication port character receiving timeout time, unit: ms	R/W	Yes	0
SV854	COM4 communication port character receiving timeout time, unit: ms	R/W	Yes	0
SV855	COM5 communication port character receiving timeout time, unit: ms	R/W	Yes	0

Set the communication port character receive timeout time using MOV instruction

Note:

- Four series of CTHN can be set separately, S series does not support setting the communication parameters.
- Communication port character receiving timeout time is used for PLC master station, there is no need to use this communication system register when PLC is used as a slave station.

9. When PLC is used as slave station, there is no need to to write any communication program, and supporting a variety of human-machine interfaces and configuration softwares

CPU host which is built-in Ethernet port and two serial ports can be extended to the Ethernet port plus five serial ports, each communication port can be programmed and networked, also it can be used as master or slave. Support the networking ways of 1: N, N: 1, N: N, support a variety of human-machine interfaces and configuration softwares, also it can be networked with any third-party device which has communication functions (such as inverters, instruments, bar-code readers, etc.). The figure below shows the networking way of N:1 when the PLC is used as a slave:



There is no need to write any program when PLC is used as slave, the default parameter is 19200 N 8 2 RTU, station number is 1. For configuration software and touch screen, which has the built-in Haiwell driver can directly select Haiwell driver, if there is no Haiwell driver, you can choose Modicon's Modbus driver. The corresponding Modbus communication code table of Haiwell is as the following figure:

Haiwell PLC bit component table (equivalent to Modbus address type of 0,1, supporting Modbus function code of 1, 2, 5, 15)

Component	Nomo	Papao	Read/Write	Modbus communicat	ion address code	Description
Component	Name	Range	attribute	Hexadecimal	Decimal	Description
Х	Digital input	X0~X1023	read	0x0000~0x03FF	0~1023	
Y	Digital output	Y0~Y1023	read/write	0x0600~0x09FF	1536~2559	
М	Auxiliary relay	M0~M12287	read/write	0x0C00~0x3BFF	3072~15359	
Т	Timer (coil)	T0~T1023	read/write	0x3C00~0x3FFF	15360~16383	
С	Counter (coil)	C0~C255	read/write	0x4000~0x40FF	16384~16639	
SM	System Status bit	SM0~SM215	all be read/some be wrote	0x4200~0x42D7	16896~17111	
S	Step relay	S0~S2047	read/write	0x7000~0x77FF	28672~30719	

② Haiwell PLC register component table (equivalent to Modbus address type of 3, 4, supporting Modbus function code of 3,4,6,16)

Component	omponent Name Bangd		Read/Write	Modbus communication address code		Description
Component	Name	Range	attribute	Hexadecimal	Decimal	Description
CR	Expansion module parameters	CR0~CR255	all be read/some be wrote	0x00~0xFF	0~255	Used when Modbus accesses expansion module parameters
AI	Analog input register	AI0~AI255	read	0x0000~0x00FF	0~255	
AQ	Analog output register	AQ0~AQ255	read/write	0x0100~0x01FF	256~511	
V	Internal data register	V0~V14847	read/write	0x0200~0x3BFF	512~15359	
TV	Current value of timer	TV0~TV1023	read/write	0x3C00~0x3FFF	15360~16383	
CV	Current value of counter	CV0~CV255	read/write	0x4000~0x40FF	16384~16639	Only CV48~CV79 are 32-bit register
SV	System register	SV0~SV900	all be read/ some be wrote	0x4400~0x4784	17408~18308	

3 Description:

- Haiwell PLC adopts standard Modbus protocol (supporting RTU and ASCII format) it can communicate with all HMI and configuration softwares that support Modbus protocol.
- Haiwell PLC's Modbus address number starts from 0, some HMI or configuration software starts from 1, if HMI

or configuration software's Modbus address starts from 0, then it directly uses the communication address, for example M0 is 0x3072, V0 is 4x0512; If the Modbus address of the HMI or configuration software starts from 1, the component address number needs to be increased by 1, for example, M0 is 0x3073 [3072 + 1] and V0 is 4x0513 [512 + 1]. The first digit of the address is the Modbus protocol component type (0/1 is bit component, 3/4 is register component, type 0/4 means read-write, type 1/3 means read-only), the rest of the digit is the component address number.

10. How to judge the communication failure and program analysis when PLC is used as slave

The communication disconnection alarm program when the master station of PLC communicates with instruments has been introduced in the above example of "Haiwellbus communication example introduction: communication between two Haiwell host PLC", then when the slave station of PLC communicates with the host computer, if communication line is broken, or the host computer parameters have been modified, at this time, as a slave of PLC, how to check the communication disconnection? The following ideas:

The host computer constantly writes M900 as OFF to PLC, the program sets M900 every second. T0 is used for host computer communication failure alarm. If the M900 has a delay of 3 seconds before getting electricity, it means the host computer does not write M900 to be OFF, so that we can judge that the communication between the host computer and the PLC fails.

//Network 1 The host computer reset M900 for to PLC, the program every second set M900



11. Check-code calculator usage introduction

If you want to use serial debugging tools or host computer to read the V100 data of Haiwell PLC, what data commands need to be sent?

According to the previous introduction we know that Haiwell PLC is built-in Modbus communication protocol, and Haiwell programming software provides a very convenient tool of check code calculator, the tool can quickly and efficiently calculate the command frame which has been sent. Open Haiwell programming software-Tools-check code calculator, pop-up the following window:

ommand				
Function code:	Read holdin	g registers		~
Component type:	v v	Component number		● RTU () ASCI
Station address:	1 🗘	Length	1 🗘	Generate
01 03 02 64 00 01 C4 6D)			~
				~
a als a antant/A a a ardin a ta	how buto inn	ut use bleek bebuses ou	ini hida auah	00.01.14 E4 EE)
eck content(According to	hex. byte inp	ut,use blank between eve	ery byte, such	as 01 1A E4 EF)
eck content(According to	hex. byte inp	ut,use blank between ev	ery byte,such	as 01 1A E4 EF)
eck content(According to	hex. byte inp	ut,use blank between ev	ery byte,such	as 01 1A E4 EF)
eck content(According to	hex. byte inp	ut,use blank between ev	ery byte,such	as 01 1A E4 EF)
eck content(According to	hex. byte inp	ut,use blank between ev	ery byte,such	as 01 1A E4 EF)
eck content(According to	hex. byte inp	ut,use blank between ev	ery byte,such	as 01 1A E4 EF)
eck content(According to	hex. byte inp	ut,use blank between eve	vry byte,such	as 01 1A E4 EF)
eck content(According to	hex. byte inp	ut,use blank between eve	Value	as 01 1A E4 EF)
eck content(According to lata convert Decim	hex. byte inp	ut,use blank between eve	Value Bytes:	as 01 1A E4 EF)
eck content(According to lata convert Decim	hex. byte inp	ut,use blank between eve	Value Bytes: CRC16(H	as 01 1A E4 EF)
eck content(According to lata convert Decim H H	hex. byte inp	ut,use blank between eve	Value Bytes: CRC16(H CRC32(H	as 01 1A E4 EF)
eck content(According to lata convert Decim H H	hex. byte inp	ut,use blank between eve	Value Bytes: CRC16(H CRC32(H	as 01 1A E4 EF)
eck content(According to lata convert Decim H Signed decim	hex. byte inp	ut,use blank between eve	Value Bytes: CRC16(H CRC32(H LRC(H	as 01 1A E4 EF)
eck content(According to lata convert Decim H Signed decim Unsigned decim	hex. byte inp	ut,use blank between eve	Value Bytes: CRC16(H CRC32(H LRC(H BCC(H)

We choose the function code, set the type of components, component number, station number of slave PLC and so on, then click generate, you can get the command: 01 03 02 64 00 01 C4 6D, the command which sent by host computer can help to read the V100 value of PLC.

The check code calculator can also carry on the positional notation conversion at the same time, check the data, calculate the serial data such as CRC, LRC, SUM and other check codes, for communication engineers, this tool is a very convenient programming assistant.

12. The introduction of supportive baud rate, data format and communication instructions when PLC communication port is used as a master/slave station

12.1 PLC communication port used as a master station:

Supported by AC, AT, AH series host PLC communication port:

	Baud rate	1200, 2400, 4800, 9600, 19200, 38400, 57600, 115200
AC/AT/AH host PLC communication port	Data format	N,8,2 RTU, E,8,1 RTU, O,8,1 RTU, N,7,2 ASCII, E,7,1 ASCII, O,7,1 ASCII, N,8, 1 RTU
	Communication instruction	MODR / MODW / HWWR / HWRD / COMM / RCV / XMT
Description: Host PLC' co	mmunication port, that is, COM1	: RS232 (round-mouth); COM2: RS485 (terminal of A + B-).

Supported by A01RS communication expansion module:

	Baud rate	1200, 2400, 4800, 9600, 19200, 38400, 57600, 115200	
A01RS communication module	Data format	N,8,2 RTU, E,8,1 RTU, O,8,1 RTU, N,7,2 ASCII, E,7,1 ASCII, O,7,1 ASCII, N,8, 1 RTU	
	Communication instruction	MODR / MODW / HWWR / HWRD / COMM	

12.2 PLC communication port used as a slave station:

Supported by AC, AT, AH series host PLC communication port:

AC/AT/AH host PLC	Baud rate	1200, 2400, 4800, 9600, 19200, 38400, 57600, 115200
communication port	Data format	N,8,2 RTU, E,8,1 RTU, O,8,1 RTU, N,7,2 ASCII, E,7,1 ASCII, O,7,1 ASCII, N,8, 1 RTU
Description: The default is	19200, N, 8,2 RTU. Generally u	se the default, without modification.

Supported by A01RS communication expansion module:

A01RS communication	Baud rate	1200, 2400, 4800, 9600, 19200, 38400, 57600	
module	Data format	N,8,2 RTU, E,8,1 RTU, O,8,1 RTU, N,7,2 ASCII, E,7,1 ASCII, O,7,1 ASCII	
Description: The default is	s 19200, N, 8,2 RTU. Generally ι	ise the default, without modification.	

13. PLC communication common problems

(1) In order to read the register value of instrument, Modbus address is 40001, in Haiwell Modbus, how much to fill in Read of read instruction MODR?

A: Fill in 0. The first digit of the address is the Modbus protocol component type (0/1 is bit component, 3/4 is register component, type 0/4 means read-write, type 1/3 means read-only), the rest of the digits are component address numbers. Besides, there is no need to add 1 when Haiwell PLC reads Modbus device address, so as for the address 40001, it only fills 0 in Read terminal as Haiwell PLC reading. Similarly, for example, an address is 40387, then as long as fill 386 in Haiwell instructions.



(2) How to set PLC station number address?

A: Address: 1~247 can be set; PLC address is divided into soft address and hard address, soft address has the highest priority.

Soft address: Through the programming software-PLC-set PLC parameters, check the use of PLC soft address, address range is 1-247;

PLC Name:	HaiwellP	LC	(Six chinese or twelve english)
Scan timeout	200	\$	ms
🔽 Use PLC so	oft addres	ss	
PLC Address:	1 2		

Hard address: The address is set through the 4-bit DIP switch of module hardware, address range 1-15. Hardware address setting example:



Where can we find Haiwell PLC online tutorial? (Haiwell official website-en.haiwell.com)
 A: Haiwell official website-Supports-FAQ "PLC online steps described in detail and online problem solution"

(4) Where can we find the communication example program between Haiwell PLC and other manufacturers' frequency converter instrument?

A: Haiwell official website-Download-Program example "Haiwell PLC program example.rar"

- Where can we find the communication example program between Haiwell PLC and other configuration software, text or HMI?
 A: Haiwell official website-Download-Program example "Communication example between Haiwell PLC and other configuration software, text or HMI.zip"
- Where can we find the communication wiring diagram between Haiwell PLC and other manufacturers' HMI?
 A: Haiwell official website-Download-User Manual "communication wiring diagram between Haiwell PLC and other manufacturers' HMI"

Thanks for choosing Haiwell Products, If you have any questions about our products or services, please let us know! Haiwell website: www.haiwell.com Copyright © 2005 Xiamen Haiwell Technology Co.,Ltd. Version - 2023071